

OVERVIEW



SPECIFICATIONS

| | | | |
|-------------------|--------------------------------|--------------------------------|---------------------------|
| Motor | External Rotor Brushless Motor | Material | Aircraft aluminum |
| Stroke Length | 3.5 mm | Operating Voltage | 5.0 - 12 V DC |
| Rpm | 9000rpm \pm 10% | Switch Frequency | 60 - 150 Hz |
| Needle Protrusion | 0 - 4.5 mm | Dimensions(\varnothing X L) | 33 x 135 mm |
| Weight | 6.96 oz (197g) with power pack | Power pack Working Time | Approx. Up to 450 Minutes |
| Battery Capacity | 1600 mAh | Recharging Time | 3.5 Hours |

THANK YOU FOR YOUR PURCHASE!

WWW.EZTATTOOSUPPLY.COM






 EZTATTOO OFFICIAL

Created and manufactured in China by EZ


BASIC OPERATION

Power ON/ OFF

Press and Hold the  button for two seconds to turn EvoTech on.



Press and Hold the  button for two seconds to power EvoTech off.

Power Start/ Stop


Click  button to turn your machine Stop/ Go.

Adjusting Voltage

Press  or  to adjust in 0.1V increments.

Press and Long Hold  or  to quickly adjust the voltage in 0.1V increments.




Changing Voltage Presets




DbClick  button EvoTech will toggle between the voltage presets.

1. Screen display "Lnr" preset LINER voltage.
2. Screen display "Shd" preset SHADER voltage.

Note: The EvoTech will adjust the voltage to the saved voltage setting you stop on, the machine startup voltage is the preset for the last shutdown.

Push Mode

Press  and  button at the same time, Screen LOGO  solid, the machine ACTIVE the strong start mode.


Press  and  button at the same time, Screen LOGO  flashes, the machine push mode OFF.

Note: In push mode the initial voltage output is 12V lasts for 1 second and then returns to normal voltage after.

Memory Function

The EvoTech will adjust the voltage to the saved voltage setting you stop on. The startup voltage is the preset voltage for the last shutdown.

Start/Stop Timer

Press  button to active your machine ON, the timing mode start. Note: timer mode record in minutes, the maximum recording time is 999 minutes. The timer will reset the count when the EvoTech Power pack is being restarted.

INCLUDED:

User Guide, EvoTech X1, Extra Grip X1, Ping plug RCA connector, RCA female connector, Battery Type-C charging cable.

NOTICE

to reduce the risk of injury, the user must read and understand the User manual before using this product, Save these instructions for future reference.

-We recommended that use the included charging cable.

-This device don't support fast charging/super fast charging,

fast charging may get damage the battery.

BATTERY PROTECTION

The battery circuitry protects the battery pack from extreme temperature, overdischarge, and over-charge. To protect the battery from damage and prolong its life, the battery pack circuitry will turn off the battery pack if it becomes overloaded or if the temperature becomes too high during use. This may happen in extremely high torque, binding, and stalling situations. The battery pack will shut down for 10s when its operating temperature exceeds 158°F (70°C), and will begin normal operation when it returns to 152°F (67°C).

NOTICE: A significantly reduced run time after fully charging the battery pack indicates that the batteries are near the end of their usable life and must be replaced.

NOTICE: Lithium-Ion battery packs are shipped partially charged. Before using it the first time, fully charge the battery pack.

WARRANTY INFORMATION

If you find that the product is malfunctioning during the warranty period, EZ provides a one-year warranty for the **EvoTech Wireless Pen Machine** purchased in our online store or authorized distributors worldwide from the date of purchase. Please contact our After-Sales Team
Email: sales@eztattooing.com.

Warranties do not cover:

- Damage to the product due to a human factor
- Product damage due to external electrical failure or any accident

WARRANTY CARD

PRODUCT NAME : _____

DATE OF PURCHASE : _____

WHERE PURCHASED : _____

ADDRESS : _____

EMAIL : _____

MY SIGNATURE BELOW ACKNOWLEDGES THAT I HAVE READ, FULLY UNDERSTAND, AND ACCEPT THIS LIMITED WARRANTY AGREEMENT.

SIGNATURE : _____ DATE : _____

SENT THIS COPY TO :
EZTATTOO - AFTER-SALES DEPARTMENT
4/F BUILDING 7 (7DONG), NO.289 FAHUA NORTH ROAD,
JINYI DUSHI NEW DISTRICT, JINHUA 321036
ZHEJIANG CHINA
TEL: +86-153-9755-3908
Email: sales@eztattooing.com