



S917

Features

- Android 8.1 ,Qualcomm, 8 core, 1.8GHz CPU/A53
- 8 inch LCD screen, 1920x1200 IPS
- 3G/4G, WIFI, Bluetooth, dual SIM card
- CCC/CE/ROSH/FCC/IP65/MIL-STD-810
- -Multifunction1D/2D bar code scanning
- HF/UHF RFID reader
- Fingerprint identification(Front)
- High precise GPS
- Wireless Charging
- Dual SIM cards

Application



Mobile office



Medical industry



Bank



Electric power



Asset management

Email: export@senter.com.cn
Tel: +86 (0)533 3589257

SENER

Specification

Operating System	Android 8.1 with google play store
CPU	Qualcomm SD630,CPU 1.8GHz /A53 Octa core
RAM	RAM:3G FLASH:32G
Extended Storage	Micro SD, Maximum 128G
Display Screen	8 inch LCD capacitive touch screen Resolution 1920*1200
USB port	5 pin MicroUSB;Support to connect OTG line
External port	Charge port and headphone port



Wireless Communication

WIFI	Support IEEE 802.11a/b/g/n/ac, 2.4G and 5G
Bluetooth	Support 4.0
2G/3G/4G	CDMA 1X/EVDO:BC0 GSM: B2/B3/B5/B8 WCDMA: B1/B2/B5/B8 TD-SDMA: 34/39 LTEB1/B3/B5/B7/B8/B20/B26/B34/B38/B39 /B40/B41

Data acquisition

GPS	GPS+BDS+A-GPS+GLONASS accuracy 10m
High precise GPS	Accuracy:3m(Optional)
Fingerprint	Support, in the front(Optional)
Barcode Scanning	1D/2D Barcode Scanner (Optional)
RFID	HF RFID UHF RFID(Optional)
Infrared meter	Support(Optional)

<https://reunit.ru/>

Protection Grade

Industrial Protection Grade	IP65
Drop Grade	Drop resistance from 1.2m

Power supply

Battery	3.8V, 6000mAh
Standby	About 500 hours Support Qi protocol wireless charging.
Dimension	229.4*136.2*11.5mm
Weight	520g

Physical parameters

Keyboard	Android menu, Homepage, Return, Volume, ON/OFF, Reset
Camera	5MP/13MP automatic focus and lighting function
Headset	3.5mm audio Interface with MIC and Single loudspeaker

Environmental Characteristics

Working Temperature	-20°C ~ +55°C	LED indicator light	Support
Storage Temperature	-40°C ~ +60°C	Flashlight Function	Support can be used for emergency lighting
Humidity	5%-95% relative humidity; no condensation	Compass	Support
		Acceleration sensors	Support
		FM	Support